MOTOROLA

MRF485

The RF Line

15 W (PEP) — 15 W (CW) — 30 MHz

RF POWER TRANSISTOR

NPN SILICON

4.1

NPN SILICON RF POWER TRANSISTOR

. . . designed primarily for use in single sideband linear amplifier output applications and other communications equipment operating to 30 MHz.

- Characterized for Single Sideband and Large-Signal Amplifier Applications Utilizing Low-Level Modulation
- Specified 28 V, 30 MHz Characteristics —
  Output Power = 15 W (PEP)
  Minimum Efficiency = 40% (SSB)
  Minimum Power Gain = 10 dB (PEP & CW)





STYLE 1:
PIN 1. BASE
2. COLLECTOR
3. EMITTER
4. COLLECTOR

NOTE:
1. DIM. L & H APPLIES TO ALL LEADS.

DIM	MILLIMETERS MIN	MILLIMETERS MAX	INCHES MIN	INCHES MAX
A	15.11	15.75	0.595	0.620
B	9.78	10.03	0.385	0.395
C	4.06	4.82	0.160	0.190
D	0.64	0.89	0.025	0.035
F	3.61	3.73	0.142	0.147
G	2.41	2.67	0.095	0.105
H	2.79	3.30	0.110	0.130
J	0.36	0.56	0.014	0.022
K	12.70	14.27	0.500	0.562
L	1.14	1.27	0.045	0.050
N	4.83	5.33	0.190	0.210
Q	2.54	3.04	0.100	0.120
R	2.04	2.79	0.080	0.110
S	1.14	1.39	0.045	0.055
T	5.97	6.48	0.235	0.255
U	0.76	1.27	0.030	0.050

CASE 221A-02
TO-220AB

MAXIMUM RATINGS

Rating	Symbol	Value	Unit
Collector-Emitter Voltage	V_{CEO}	35	Vdc
Collector-Base Voltage	V_{CBO}	65	Vdc
Emitter-Base Voltage	V_{EBO}	4.0	Vdc
Collector Current — Continuous	I_C	1.0	Adc
Total Device Dissipation @ $T_C = 50^oC$ (1) Derate above 50^oC	P_D	30 0.3	Watts $W/^oC$
Storage Temperature Range	T_{stg}	−65 to +150	^oC

THERMAL CHARACTERISTICS

Characteristic	Symbol	Max	Unit
Thermal Resistance, Junction to Case	$R_{\theta JC}$	3.33	$^oC/W$

(1) These devices are designed for RF operation. The total device dissipation rating applies only when the devices are operated as RF amplifiers.